



From Tyco Security Products

## Wireless Photoelectric Smoke Detector **WS4916**



### Features That Make a Difference:

- Automatic drift compensation
- Built-in, dual-sensor heat detector
- Built-in 85dB horn
- Local test button
- Low profile design
- High/Low sensitivity reporting
- Low battery indication
- Easy-maintenance removable smoke chamber
- Non-contact sensitivity testing with FSD-100 handheld test meter
- Long-life lithium batteries included
- UL/ULC/EN listed for commercial and residential applications
- Compatible with all DSC 433 MHz wireless receivers

Designed to provide reliable smoke detection, the WS4916 is a low-profile wireless photoelectric smoke detector that is ideal for difficult-to-wire residential or commercial applications.

The WS4916, compatible with all DSC 433 MHz wireless receivers, features a built-in alarm horn, integral dual-sensor heat detection, automatic drift compensation and an easy-maintenance removable smoke chamber. Long-life lithium batteries provide extended operation without replacement. Precise and quick sensitivity testing of the unit is easily accomplished with the FSD-100 handheld test meter.

### Easy Installation

The WS4916 is ideal for residential or commercial applications where running wire to a smoke detector is either difficult or impossible. With

no wires to run, installers are able to save time and move more quickly through the installation process. All the WS4916 requires for installation is a screwdriver and any DSC 433 MHz wireless receiver.

### False Alarm Reduction

DSC is committed to reducing false alarms and has integrated a number of features into the WS4916 to provide reliable detection. One important feature is drift compensation. It provides a constant level of sensitivity performance for extended operation. As dust accumulates in a detector it adjusts to maintain the original factory-set sensitivity, thereby minimizing the potential for false alarms. If the detector reaches its limit of compensation, it will indicate a trouble condition well before the sensitivity increases to a level where false alarms will be generated.

sensors and accessories



From Tyco Security Products

## Non-Contact Sensitivity Testing

Precise and quick sensitivity testing is easily accomplished with the non-contact FSD-100 handheld test meter. Powered by a standard 9V alkaline battery and small enough to fit inside a shirt pocket, the FSD-100 holds 500 readings that can be downloaded to any computer. To initiate a reading, a technician simply holds the FSD-100 near a DSC smoke detector and activates the detector's test button.

## Value Added

The WS4916 is built with reliable 433 MHz technology and ships with two long-life lithium batteries (3V) that are activated by the installer upon purchase.

## Compatibility

- IMPASSA Self-Contained 2-Way Wireless Security System
- ALEXOR 2-Way Wireless Security System
- SCW9045/9047 Self-Contained Wireless Security System
- PowerSeries Wireless Receivers PC5132-433 / RF5132-433 / RF5108-433 / TR5164-433
- PowerSeries RFK Keypads RFK55XX-433
- MAXSYS Wireless Receivers PC4164-433 / RF4164-433
- WS4920 Wireless Repeater

## Specifications

Diameter.....	5.8" (147 mm)
Height .....	2.08" (52.8 mm)
Battery .....	2 x CR123A (3V Lithium)
Mounting.....	Surface mount with screws
Nominal.....	3.0% +/- 0.8% obscuration/ft. (UL)
Nominal.....	2.0% +/- 0.5% obscuration/ft. (ULC & EN)
Alarm.....	Fixed-Temperature 57.2°C (135°F)
Operating Temperature.....	0° to 38°C (32° to 100°F)
Relative Humidity .....	5% to 95%